

MiTrek VHF 2 Meter - Control Head Wiring and Packet DIN Connector

3/26/94

MiTrek Radio Connector Block		TNC-200 DIN Connector Plug		Signal
Pin	Wire Color	Wire Color	DIN Pin	Function
1	Brown (Center of Red Shield)	Center	DIN5-1	Xmit Audio to MIC
2	Red Shield, Bare Shield Foil			
3	Orange			
4	Yellow			
5	Green			
6	Blue, Stiff Maroon to Pin 17	Shields	DIN5-2	GROUND
7	Purple			
8	Gray			
9	White			
10	Black			
11	Black/Brown			
12	Black/Red			
13	Black/Orange	Center	DIN5-3	PTT
14	Black/Yellow			
15	Black/Green			
16	Black/Blue			
17	Black - POWER, Stiff Maroon to Pin 6 Black/Purple			
18	Black/Gray			
19	Red - POWER			
	From Speaker Audio Transformer - RCA Phono	Center	DIN5-4	Receive Audio from Speaker